

**Bosch Hi Speed Air  
Temperature Sensor  
P/N H-ATHS**

Drawing Revision 1 - 20/6/2016



[www.youtube.com/efihardware](http://www.youtube.com/efihardware)



[www.facebook.com/efihardware](http://www.facebook.com/efihardware)



[www.efihardware.com](http://www.efihardware.com)



[info@efihardware.com](mailto:info@efihardware.com)



(03) 9873 5400  
+613 9873 5400



(03) 9873 5955  
+613 9873 5955

**Temperature (°C) Vs Resistance (Ω)**

-40	25.1K	70	0.39K
-30	16.9K	80	0.29K
-20	11.4K	90	0.21K
-10	7.7K	100	0.17K
0	5.2K	110	0.14K
10	3.5K	120	0.11K
20	2.4K	130	0.10K
30	1.7K		
40	1.1K		
50	0.78K		
60	0.55K		

**NOTES:**

TEMPERATURE SENSOR HOLE: 12.5mm  
FASTENING HOLE: M6  
TEMP SENSOR TO FASTENING HOLE: 15mm

