

**Air Temp Sensor - Delco**  
**Technical Diagram**  
**Part Number: H-ATS**  
**Drawing Revision 1 - 31/5/2019**



[www.youtube.com/efihardware](http://www.youtube.com/efihardware)



[www.facebook.com/efihardware](http://www.facebook.com/efihardware)



[www.efihardware.com](http://www.efihardware.com)




[info@efihardware.com](mailto:info@efihardware.com)



(03) 9873 5400  
+613 9873 5400



(03) 9873 5955  
+613 9873 5955



**NOTES:**

**M14x1.5**

**19mm Hex**

**Connector**

- H-ATC (pull to seat terminals)**
- H-ATCX (push to seat terminals)**

**Alloy weld on bung**  
**H-ATB**

**Unloaded Resistance Vs Temperature Data Table**

Temp C	R Ohms	Volts	Temp C	R Ohms	Volts	Temp C	R Ohms	Volts
-40	99,326	4.90	25	2,752		90	238.1	0.96
-35	71,332		30	2,205	3.16	95	203.9	
-30	51,791	4.85	35	1,778		100	175.3	0.74
-25	37,994		40	1,443	2.94	105	151.3	
-20	28,146	4.78	45	1,177		110	131.0	0.58
-15	21,044		50	965	2.44	115	113.9	
-10	15,873	4.66	55	796		120	99.4	0.45
-5	12,073		60	660	1.98	125	87.0	
0	9,256	4.47	65	551		130	76.4	0.35
5	7,153		70	462	1.57	135	67.3	
10	5,572	4.20	75	389		140	59.4	0.28
15	4,373		80	329	1.23	145	52.6	
20	3,457	3.85	85	279		150	46.7	0.22

**EFI Hardware Mobile Apps**



[www.efihardware.com/apps.php](http://www.efihardware.com/apps.php)